



UTXB0104

Preliminary

CMOS IC

4-BIT BIDIRECTIONAL VOLTAGE-LEVEL TRANSLATOR WITH AUTOMATIC DIRECTION SENSING

■ DESCRIPTION

The UTC **UTXB0104** is 4-bit non-inverting translator uses two separate configurable power-supply rails. The A port is designed to track V_{CCA} . V_{CCA} accepts any supply voltage from 1.2V to 3.6V. The B port is designed to track V_{CCB} . V_{CCB} accepts any supply voltage from State 1.65V to 5.5V. This allows for universal low Voltage bidirectional translation between any of the 1.2V, 1.5V, 1.8V, 2.5V, 3.3V, and 5V voltage nodes. V_{CCA} should not exceed V_{CCB} .

When the output-enable (OE) input is low, all outputs are placed in the high-impedance state. To ensure the high-impedance state during power up or power down, OE should be tied to GND through a pull-down resistor; the minimum value of the resistor is determined by the current-sourcing capability of the driver.

The **UTC UTXB0104** is designed so that the OE input circuit is supplied by V_{CCA} .


This device is fully specified for partial-power-down applications using I_{OFF} circuitry disables the outputs, preventing damaging current backflow through the device when it is powered down.

■ FEATURES

- * 1.2V to 3.6V on A Port and 1.65V to 5.5V on B Port
($V_{CCA} \leq V_{CCB}$)
- * V_{CC} Isolation Feature – If Either V_{CC} Input Is at GND, All Outputs Are in the High-Impedance State
- * OE Input Circuit Referenced to V_{CCA}
- * Low Power Consumption, 5 μ A Max I_{CC}
- * I_{OFF} Supports Partial-Power-Down Mode Operation

■ APPLICATION

- * Headset
- * Smartphone
- * Tablet
- * Desktop PC



ORDERING INFORMATION


Ordering Number		Package	Packing
Lead Free	Halogen Free		
UTXB0104L-UEA-R	UTXB0104G-UEA-R	SOP-14U	Tape Reel
UTXB0104L-UEB-R	UTXB0104G-UEB-R	TSSOP-14U	Tape Reel
UTXB0104L-QAC-R	UTXB0104G-QAC-R	X1QFN-12(1.7×2.0)	Tape Reel
UTXB0104L-QAJ-R	UTXB0104G-QAJ-R	QFN-14(3.5×3.5)	Tape Reel

UTXB0104G-UEA-R (1) Packing Type (2) Package Type (3) Green Package	(1) R: Tape Reel (2) UEA: SOP-14U, UEB: TSSOP-14U, QAC: X1QFN-12(1.7×2.0), QAJ: QFN-14(3.5×3.5) (3) G: Halogen Free and Lead Free, L: Lead Free
---	--



MARKING

SOP-14U	TSSOP-14U
UTC □ □ □ □ → Date Code L: Lead Free G: Halogen Free □ □ → Lot Code	UTC □ □ □ □ → Date Code L: Lead Free G: Halogen Free □ □ → Lot Code
X1QFN-12(1.7×2.0)	QFN-14(3.5×3.5)
B04	UTC UTXB0104 □ → L: Lead Free G: Halogen Free □ □ → Lot Code □ □ □ □ → Date Code

PIN CONFIGURATION



SOP-14U / TSSOP-14U

X1QFN-12(1.7×2.0)
(TOP View)QFN-14(3.5×3.5)
(TOP View)

PIN DESCRIPTION

PIN NO.			PIN NAME	I/O	DESCRIPTION
SOP-14U TSSOP-14U	X1QFN-12(1.7×2.0)	QFN-14(3.5×3.5)			
1	1	1	V _{CCA}		A-port supply voltage $1.2V \leq V_{CCA} \leq 3.6V$ and $V_{CCA} \leq V_{CCB}$.
2	2	2	A1	I/O	Input/output A1. Referenced to V _{CCA}
3	3	3	A2	I/O	Input/output A2. Referenced to V _{CCA}
4	4	4	A3	I/O	Input/output A3. Referenced to V _{CCA}
5	5	5	A4	I/O	Input/output A4. Referenced to V _{CCA}
6	-	6	NC		No connection. Not internally connected.
7	6	7	GND		Ground
8	12	8	OE	I	3-state output-mode enable. Pull OE low to place all outputs in 3-state mode. Referenced to V _{CCA}
9	-	9	NC		No connection. Not internally connected.
10	7	10	B4	I/O	Input/output B4. Referenced to V _{CCB}
11	8	11	B3	I/O	Input/output B3. Referenced to V _{CCB}
12	9	12	B2	I/O	Input/output B2. Referenced to V _{CCB}
13	10	13	B1	I/O	Input/output B1. Referenced to V _{CCB}
14	11	14	V _{CCB}		B-port supply voltage $1.65V \leq V_{CCB} \leq 5.5V$
-	-	Exposed Pad	NC		Thermal pad

Note: I=Input, I/O=Input and Output.


FUNCTION TABLE

SUPPLY VOLTAGE		INPUTS	INPUTS/OUTPUT	
V _{CCA}	V _{CCB}	OE	A _n	B _n
1.2V ~ V _{CCB}	1.65V ~ 5.5V	L	Z	Z
1.2V ~ V _{CCB}	1.65V ~ 5.5V	H	Input or Output	Output or Input
GND (Note 2)	GND (Note 2)	X	Z	Z

Notes: 1. H = High voltage level ; L = Low voltage level ; Z : High impedance OFF-state ; X = Don't care.

2. When either V_{CCA} or V_{CCB} is at GND level, the device goes into Power-down mode.

■ BLOCK DIAGRAM



■ ABSOLUTE MAXIMUM RATING (Unless otherwise specified)

PARAMETER		SYMBOL	RATINGS	UNIT
Supply voltage		V_{CCA}	-0.5 ~ 4.6	V
Supply voltage		V_{CCB}	-0.5 ~ 6.5	V
Input voltage	A Port	V_{IN}	-0.5 ~ 4.6	V
	B Port		-0.5 ~ 6.5	V
Voltage range applied to any output in the high-impedance or power-off state	A Port	V_{OUT}	-0.5 ~ 4.6	V
	B Port		-0.5 ~ 6.5	V
Voltage range applied to any output in the high or low state	A Port	V_{OUT}	-0.5 ~ $V_{CCA}+0.5$	V
	B Port		-0.5 ~ $V_{CCB}+0.5$	V
Input clamp current	$V_{IN}<0$	I_{IK}	-50	mA
Output clamp current	$V_{OUT}<0$	I_{OK}	-50	mA
Continuous Output Current		I_{OUT}	±50	mA
Continuous current through V_{CCA} , V_{CCB} , or GND		I_{CC}/I_{GND}	±100	mA
Storage Temperature		T_{STG}	-65 ~ +150	°C

Note: Absolute maximum ratings are those values beyond which the device could be permanently damaged. Absolute maximum ratings are stress ratings only and functional device operation is not implied.

■ RECOMMENDED OPERATING CONDITIONS (Unless otherwise specified)

PARAMETER		SYMBOL	TEST CONDITIONS	MIN	TYP	MAX	UNIT
Supply Voltage		V_{CCA}		1.2		3.6	V
Supply Voltage		V_{CCB}		1.65		5.5	V
Input Voltage		V_{IN}		0		V_{CCI}	V
Output Voltage	A Port	V_{OUT}	$V_{CCA}=1.2V\sim3.6V$, $V_{CCB}=1.65V\sim5.5V$	0		3.6	V
	B Port		$V_{CCA}=1.2V\sim3.6V$, $V_{CCB}=1.65V\sim5.5V$	0		5.5	V
High-Level Input Voltage	Data Inputs	V_{IH}	$V_{CCA}=1.2V\sim3.6V$, $V_{CCB}=1.65V\sim5.5V$	V_{CCI} ×0.65 (Note 3)		V_{CCI}	V
	OE			V_{CCA} ×0.65		5.5	V
Low-Level Input Voltage	Data Inputs	V_{IL}	$V_{CCA}=1.2V\sim3.6V$, $V_{CCB}=1.65V\sim5.5V$	0		V_{CCI} ×0.35 (Note 3)	V
	OE			0		V_{CCA} ×0.35	V
Input Transition Rise or Fall Rate	A Port Inputs	$\Delta t/\Delta v$	$V_{CCA}=1.2V\sim3.6V$	$V_{CCB}=1.65V\sim5.5V$		40	ns/V
	B Port Inputs			$V_{CCB}=1.65V\sim3.6V$		40	ns/V
	Inputs			$V_{CCB}=4.5V\sim5.5V$		30	ns/V
Operating Temperature		T_A		-40		+125	°C

Notes: 1. The A and B sides of an unused data I/O pair must be held in the same state, i.e., both at V_{CCI} or both at GND.

2. V_{CCA} must be less than or equal to V_{CCB} and must not exceed 3.6V.

3. V_{CCI} is the supply voltage associated with the input port.

■ ELECTRICAL CHARACTERISTICS (Unless otherwise specified)

PARAMETER		SYMBOL	TEST CONDITIONS		MIN	TYP	MAX	UNIT
Port A Output High Voltage		V _{OHA}	V _{CCA} =1.2V, I _{OH} =-20μA			1.1		V
			V _{CCB} =1.4V~3.6V, I _{OH} =-20μA		V _{CCA} -0.4			V
Port A Output Low Voltage		V _{OLA}	V _{CCA} =1.2V, I _{OL} =20μA			0.3		V
			V _{CCB} =1.4V~3.6V, I _{OL} =20μA				0.4	V
Port B Output High Voltage		V _{OHB}	V _{CCB} =1.65V~5.5V, I _{OH} =-20μA		V _{CCB} -0.4			V
Port B Output Low Voltage		V _{OLB}	V _{CCB} =1.65V~5.5V, I _{OL} =20μA				0.4	V
Input Leakage Current	OE	I _{I(LEAK)}	V _I =V _{CCI} or GND, V _{CCA} =1.2V~3.6V, V _{CCB} =1.65V~5.5V				±1	μA
Power OFF Leakage Current	A Port	I _{OFF}	V _I or V _{OUT} =0~3.6V, V _{CCA} =0V, V _{CCB} =0V~5.5V				±1	μA
	B Port		V _I or V _{OUT} =0~5.5V, V _{CCA} =0V~3.6V, V _{CCB} =0V				±1	μA
High-Impedance State Output Current	A or B Port	I _{OZ}	V _{CCA} =1.2V~3.6V, V _{CCB} =1.65V~5.5V, OE=GND				±1	μA
Quiescent Supply Current		I _{CCA}	V _I =V _{CCI} or GND I _O =0A	V _{CCA} =1.2V, V _{CCB} =1.65V~5.5V		0.06		μA
				V _{CCA} =1.4V~3.6V, V _{CCB} =1.65V~5.5V			5	μA
				V _{CCA} =3.6V, V _{CCB} =0V			2	μA
				V _{CCA} =0V, V _{CCB} =5.5V			-2	μA
		I _{CCB}		V _{CCA} =1.2V, V _{CCB} =1.65V~5.5V		3.4		μA
				V _{CCA} =1.4V~3.6V, V _{CCB} =1.65V~5.5V			5	μA
				V _{CCA} =3.6V, V _{CCB} =0V			-2	μA
				V _{CCA} =0V, V _{CCB} =5.5V			2	μA
		I _{CCA} +I _{CCB}		V _{CCA} =1.2V, V _{CCB} =1.65V~5.5V		3.5		μA
				V _{CCA} =1.4V~3.6V, V _{CCB} =1.65V~5.5V			10	μA
		I _{CCZA}		V _{CCA} =1.2V, V _{CCB} =1.65V~5.5V OE=GND		0.05		μA
				V _{CCA} =1.4V~3.6V, V _{CCB} =1.65V~5.5V OE=GND			5	μA
		I _{CCZB}		V _{CCA} =1.2V, V _{CCB} =1.65V~5.5V OE=GND		3.3		μA
				V _{CCA} =1.4V~3.6V, V _{CCB} =1.65V~5.5V OE=GND			5	μA
Input Capacitance	OE	C _{IN}	V _{CCA} =1.2V~3.6V, V _{CCB} =1.65V~5.5V			3		pF
Output Capacitance	A Port	C _{IO}				5		pF
	B Port					11		pF

Notes: 1. V_{CCI} is the supply voltage associated with the input port.2. V_{CCO} is the supply voltage associated with the output port.3. V_{CCA} must be less than or equal to V_{CCB} , and V_{CCA} must not exceed 3.6V.

■ SWITCHING CHARACTERISTICS (Unless otherwise specified)

PARAMETER	SYMBOL	TEST CONDITIONS		MIN	TYP	MAX	UNIT
Propagation Delay From Input (A) to Output (B)	t_{PD}	$V_{CCA}=1.2V$	$V_{CCB}=1.8V$		8.9		ns
			$V_{CCB}=2.5V$		7.7		ns
			$V_{CCB}=3.3V$		7.3		ns
			$V_{CCB}=5V$		7.5		ns
		$V_{CCA}=1.5V\pm0.1V$	$V_{CCB}=1.8V\pm0.15V$	1.4		14.4	ns
			$V_{CCB}=2.5V\pm0.2V$	1.2		11.6	ns
			$V_{CCB}=3.3V\pm0.3V$	1.1		11.5	ns
			$V_{CCB}=5V\pm0.5V$	0.8		11.4	ns
		$V_{CCA}=1.8V\pm0.15V$	$V_{CCB}=1.8V\pm0.15V$	1.6		12	ns
			$V_{CCB}=2.5V\pm0.2V$	1.4		8.7	ns
			$V_{CCB}=3.3V\pm0.3V$	1.3		7.8	ns
			$V_{CCB}=5V\pm0.5V$	1.2		7.5	ns
		$V_{CCA}=2.5V\pm0.2V$	$V_{CCB}=2.5V\pm0.2V$	1.1		7	ns
			$V_{CCB}=3.3V\pm0.3V$	1.0		5.9	ns
			$V_{CCB}=5V\pm0.5V$	0.9		5.4	ns
		$V_{CCA}=3.3V\pm0.3V$	$V_{CCB}=3.3V\pm0.3V$	0.9		5.2	ns
			$V_{CCB}=5V\pm0.5V$	0.8		4.5	ns
Propagation Delay From Input (B) to Output (A)	t_{PD}	$V_{CCA}=1.2V$	$V_{CCB}=1.8V$		9.4		ns
			$V_{CCB}=2.5V$		8.4		ns
			$V_{CCB}=3.3V$		8.0		ns
			$V_{CCB}=5V$		8.8		ns
		$V_{CCA}=1.5V\pm0.1V$	$V_{CCB}=1.8V\pm0.15V$	1.4		15.7	ns
			$V_{CCB}=2.5V\pm0.2V$	1.2		13.5	ns
			$V_{CCB}=3.3V\pm0.3V$	1.1		13.2	ns
			$V_{CCB}=5V\pm0.5V$	0.8		15.2	ns
		$V_{CCA}=1.8V\pm0.15V$	$V_{CCB}=1.8V\pm0.15V$	1.6		13	ns
			$V_{CCB}=2.5V\pm0.2V$	1.4		9.4	ns
			$V_{CCB}=3.3V\pm0.3V$	1.3		8.6	ns
			$V_{CCB}=5V\pm0.5V$	1.2		8.1	ns
		$V_{CCA}=2.5V\pm0.2V$	$V_{CCB}=2.5V\pm0.2V$	1.1		7.3	ns
			$V_{CCB}=3.3V\pm0.3V$	1.0		5.8	ns
			$V_{CCB}=5V\pm0.5V$	0.9		5.1	ns
		$V_{CCA}=3.3V\pm0.3V$	$V_{CCB}=3.3V\pm0.3V$	1.0		5.4	ns
			$V_{CCB}=5V\pm0.5V$	0.9		4.3	ns
Enable Time From Input (OE) to Output (A or B)	t_{en}	$V_{CCA}=1.2V$	$V_{CCB}=1.8V$		1		μs
			$V_{CCB}=2.5V$		1		μs
			$V_{CCB}=3.3V$		1		μs
			$V_{CCB}=5V$		1		μs
		$V_{CCA}=1.5V\pm0.1V$	$V_{CCB}=1.8V\pm0.15V$			1	μs
			$V_{CCB}=2.5V\pm0.2V$			1	μs
			$V_{CCB}=3.3V\pm0.3V$			1	μs
			$V_{CCB}=5V\pm0.5V$			1	μs
		$V_{CCA}=1.8V\pm0.15V$	$V_{CCB}=1.8V\pm0.15V$			1	μs
			$V_{CCB}=2.5V\pm0.2V$			1	μs
			$V_{CCB}=3.3V\pm0.3V$			1	μs
			$V_{CCB}=5V\pm0.5V$			1	μs
		$V_{CCA}=2.5V\pm0.2V$	$V_{CCB}=2.5V\pm0.2V$			1	μs
			$V_{CCB}=3.3V\pm0.3V$			1	μs
			$V_{CCB}=5V\pm0.5V$			1	μs
		$V_{CCA}=3.3V\pm0.3V$	$V_{CCB}=3.3V\pm0.3V$			1	μs
			$V_{CCB}=5V\pm0.5V$			1	μs

■ SWITCHING CHARACTERISTICS (Cont.)

PARAMETER		SYMBOL	TEST CONDITIONS		MIN	TYP	MAX	UNIT
Disable Time From Input (OE) to Output (A)		t _{dis}	V _{CCA} =1.2V	V _{CCB} =1.8V		18		ns
				V _{CCB} =2.5V		15		ns
				V _{CCB} =3.3V		14		ns
				V _{CCB} =5V		14		ns
			V _{CCA} =1.5V±0.1V	V _{CCB} =1.8V±0.15V	5.9		31	ns
				V _{CCB} =2.5V±0.2V	5.7		25.9	ns
				V _{CCB} =3.3V±0.3V	5.6		23	ns
				V _{CCB} =5V±0.5V	5.7		22.4	ns
			V _{CCA} =1.8V±0.15V	V _{CCB} =1.8V±0.15V	5.9		31	ns
				V _{CCB} =2.5V±0.2V	5.1		21.3	ns
				V _{CCB} =3.3V±0.3V	5.0		19.3	ns
				V _{CCB} =5V±0.5V	5.0		17.4	ns
			V _{CCA} =2.5V±0.2V	V _{CCB} =2.5V±0.2V	5.1		21.3	ns
				V _{CCB} =3.3V±0.3V	4.6		15.2	ns
				V _{CCB} =5V±0.5V	4.6		13.2	ns
			V _{CCA} =3.3V±0.3V	V _{CCB} =3.3V±0.3V	4.6		15.2	ns
V _{CCB} =5V±0.5V	4.3			12.1	ns			
Disable Time From Input (OE) to Output (B)		t _{dis}	V _{CCA} =1.2V	V _{CCB} =1.8V		20		ns
				V _{CCB} =2.5V		17		ns
				V _{CCB} =3.3V		16		ns
				V _{CCB} =5V		16		ns
			V _{CCA} =1.5V±0.1V	V _{CCB} =1.8V±0.15V	5.4		30.3	ns
				V _{CCB} =2.5V±0.2V	4.9		22.8	ns
				V _{CCB} =3.3V±0.3V	4.8		20	ns
				V _{CCB} =5V±0.5V	4.9		19.5	ns
			V _{CCA} =1.8V±0.15V	V _{CCB} =1.8V±0.15V	5.4		30.3	ns
				V _{CCB} =2.5V±0.2V	4.4		20.8	ns
				V _{CCB} =3.3V±0.3V	4.2		17.9	ns
				V _{CCB} =5V±0.5V	4.3		16.3	ns
			V _{CCA} =2.5V±0.2V	V _{CCB} =2.5V±0.2V	4.4		20.8	ns
				V _{CCB} =3.3V±0.3V	3.8		16	ns
				V _{CCB} =5V±0.5V	3.9		13.9	ns
			V _{CCA} =3.3V±0.3V	V _{CCB} =3.3V±0.3V	3.8		16	ns
V _{CCB} =5V±0.5V	3.4			13.2	ns			
Rise and Fall Time	A Port Rise And Fall Times	t _{rA} , t _{fA}	V _{CCA} =1.2V	V _{CCB} =1.8V		4.2		ns
				V _{CCB} =2.5V		4.2		ns
				V _{CCB} =3.3V		4.2		ns
				V _{CCB} =5V		4.2		ns
			V _{CCA} =1.5V±0.1V	V _{CCB} =1.8V±0.15V	1.4		5.1	ns
				V _{CCB} =2.5V±0.2V	1.4		5.1	ns
				V _{CCB} =3.3V±0.3V	1.4		5.1	ns
				V _{CCB} =5V±0.5V	1.4		5.1	ns
			V _{CCA} =1.8V±0.15V	V _{CCB} =1.8V±0.15V	1.0		4.2	ns
				V _{CCB} =2.5V±0.2V	1.1		4.1	ns
				V _{CCB} =3.3V±0.3V	1.1		4.1	ns
				V _{CCB} =5V±0.5V	1.1		4.1	ns
			V _{CCA} =2.5V±0.2V	V _{CCB} =2.5V±0.2V	0.8		3.0	ns
				V _{CCB} =3.3V±0.3V	0.8		3.0	ns
				V _{CCB} =5V±0.5V	0.8		3.0	ns
			V _{CCA} =3.3V±0.3V	V _{CCB} =3.3V±0.3V	0.7		2.5	ns
V _{CCB} =5V±0.5V	0.7			2.5	ns			

■ SWITCHING CHARACTERISTICS (Cont.)

PARAMETER		SYMBOL	TEST CONDITIONS		MIN	TYP	MAX	UNIT
Rise and Fall Time	B Port Rise And Fall Times	t_{rB}, t_{fB}	$V_{CCA}=1.2V$	$V_{CCB}=1.8V$		2.1		ns
				$V_{CCB}=2.5V$		1.5		ns
				$V_{CCB}=3.3V$		1.2		ns
				$V_{CCB}=5V$		1.1		ns
			$V_{CCA}=1.5V\pm0.1V$	$V_{CCB}=1.8V\pm0.15V$	0.9		4.5	ns
				$V_{CCB}=2.5V\pm0.2V$	0.6		3.2	ns
				$V_{CCB}=3.3V\pm0.3V$	0.5		2.8	ns
				$V_{CCB}=5V\pm0.5V$	0.4		2.7	ns
			$V_{CCA}=1.8V\pm0.15V$	$V_{CCB}=1.8V\pm0.15V$	0.9		3.8	ns
				$V_{CCB}=2.5V\pm0.2V$	0.6		3.2	ns
				$V_{CCB}=3.3V\pm0.3V$	0.5		2.8	ns
				$V_{CCB}=5V\pm0.5V$	0.4		2.7	ns
			$V_{CCA}=2.5V\pm0.2V$	$V_{CCB}=2.5V\pm0.2V$	0.7		2.6	ns
				$V_{CCB}=3.3V\pm0.3V$	0.5		2.8	ns
			$V_{CCA}=3.3V\pm0.3V$	$V_{CCB}=3.3V\pm0.3V$	0.5		2.1	ns
				$V_{CCB}=5V\pm0.5V$	0.4		2.7	ns
Data Rate		f_{data}	$V_{CCA}=1.2V, V_{CCB}=1.8V\sim5V$			20		Mbps
			$V_{CCA}=1.5V\pm0.1V, V_{CCB}=1.65V\sim5.5V$				40	Mbps
			$V_{CCA}=1.8V\pm0.15V, V_{CCB}=1.65V\sim5.5V$				60	Mbps
			$V_{CCA}=2.5V\pm0.2V, V_{CCB}=2.3V\sim5.5V$				100	Mbps
			$V_{CCA}=3.3V\pm0.3V, V_{CCB}=3.0V\sim5.5V$				100	Mbps
Pulse Duration	Data Inputs	t_w	$V_{CCA}=1.2V, V_{CCB}=1.8V\sim5V$			50		ns
			$V_{CCA}=1.5V\pm0.1V, V_{CCB}=1.65V\sim5.5V$		25			ns
			$V_{CCA}=1.8V\pm0.15V, V_{CCB}=1.65V\sim5.5V$		17			ns
			$V_{CCA}=2.5V\pm0.2V, V_{CCB}=2.3V\sim5.5V$		10			ns
			$V_{CCA}=3.3V\pm0.3V, V_{CCB}=3.0V\sim5.5V$		10			ns

■ OPERATING CHARACTERISTICS (Unless otherwise specified)

PARAMETER		SYMBOL	TEST CONDITIONS		MIN	TYP	MAX	UNIT	
Power Dissipation Capacitance	A Port Input B Port Output	C _{CPDA}	C _L =0, f=10MHz t _r =t _r =1nS OE=V _{CCA} (Output Enabled)	V _{CCA} =1.2V V _{CCB} =5V		7.8		pF	
				V _{CCA} =1.2V V _{CCB} =1.8V		10		pF	
				V _{CCA} =1.5V V _{CCB} =1.8V		9		pF	
				V _{CCA} =1.8V V _{CCB} =1.8V		8		pF	
				V _{CCA} =2.5V V _{CCB} =2.5V		8		pF	
				V _{CCA} =2.5V V _{CCB} =5V		8		pF	
				V _{CCA} =3.3V V _{CCB} =3.3~5V		9		pF	
				V _{CCA} =1.2V V _{CCB} =5V		12		pF	
	B Port Input A Port Output			V _{CCA} =1.2V V _{CCB} =1.8V		11		pF	
				V _{CCA} =1.5V V _{CCB} =1.8V		11		pF	
				V _{CCA} =1.8V V _{CCB} =1.8V		11		pF	
				V _{CCA} =2.5V V _{CCB} =2.5V		11		pF	
				V _{CCA} =2.5V V _{CCB} =5V		11		pF	
				V _{CCA} =3.3V V _{CCB} =3.3~5V		11		pF	
				A Port Input B Port Output	V _{CCA} =1.2V V _{CCB} =5V		0.01		pF
					V _{CCA} =1.2V V _{CCB} =1.8V		0.01		pF
	V _{CCA} =1.5V V _{CCB} =1.8V					0.01		pF	
	V _{CCA} =1.8V V _{CCB} =1.8V					0.01		pF	
	V _{CCA} =2.5V V _{CCB} =2.5V					0.01		pF	
	V _{CCA} =2.5V V _{CCB} =5V					0.01		pF	
	V _{CCA} =3.3V V _{CCB} =3.3~5V					0.01		pF	

■ OPERATING CHARACTERISTICS (Cont.)


PARAMETER		SYMBOL	TEST CONDITIONS		MIN	TYP	MAX	UNIT			
Power Dissipation Capacitance	B Port Input A Port Output	C _{PD A}	C _L =0, f=10MHz t _r =t _f =1nS OE=GND (Output Disabled)	V _{CCA} =1.2V V _{CCB} =5V		0.01		pF			
				V _{CCA} =1.2V V _{CCB} =1.8V		0.01		pF			
				V _{CCA} =1.5V V _{CCB} =1.8V		0.01		pF			
				V _{CCA} =1.8V V _{CCB} =1.8V		0.01		pF			
				V _{CCA} =2.5V V _{CCB} =2.5V		0.01		pF			
				V _{CCA} =2.5V V _{CCB} =5V		0.01		pF			
				V _{CCA} =3.3V V _{CCB} =3.3~5V		0.01		pF			
				A Port Input B Port Output	C _{PD B}	C _L =0, f=10MHz t _r =t _f =1nS OE=V _{CCA} (Output Enabled)	V _{CCA} =1.2V V _{CCB} =5V		38.1		pF
							V _{CCA} =1.2V V _{CCB} =1.8V		28		pF
	V _{CCA} =1.5V V _{CCB} =1.8V		28					pF			
	V _{CCA} =1.8V V _{CCB} =1.8V		28					pF			
	V _{CCA} =2.5V V _{CCB} =2.5V		29					pF			
	V _{CCA} =2.5V V _{CCB} =5V		29					pF			
	V _{CCA} =3.3V V _{CCB} =3.3~5V		29					pF			
	B Port Input A Port Output	V _{CCA} =1.2V V _{CCB} =5V		25.4				pF			
		V _{CCA} =1.2V V _{CCB} =1.8V		19				pF			
		V _{CCA} =1.5V V _{CCB} =1.8V		18				pF			
		V _{CCA} =1.8V V _{CCB} =1.8V		18				pF			
		V _{CCA} =2.5V V _{CCB} =2.5V		19				pF			
		V _{CCA} =2.5V V _{CCB} =5V		21				pF			
		V _{CCA} =3.3V V _{CCB} =3.3~5V		22				pF			

■ OPERATING CHARACTERISTICS (Cont.)

PARAMETER		SYMBOL	TEST CONDITIONS		MIN	TYP	MAX	UNIT
Power Dissipation Capacitance	A Port Input B Port Output	C _{PDB}	C _L =0, f=10MHz t _r =t _r =1nS OE=GND (Output Disabled)	V _{CCA} =1.2V V _{CCB} =5V		0.01		pF
				V _{CCA} =1.2V V _{CCB} =1.8V		0.01		pF
				V _{CCA} =1.5V V _{CCB} =1.8V		0.01		pF
				V _{CCA} =1.8V V _{CCB} =1.8V		0.01		pF
				V _{CCA} =2.5V V _{CCB} =2.5V		0.01		pF
				V _{CCA} =2.5V V _{CCB} =5V		0.01		pF
	B Port Input A Port Output			V _{CCA} =3.3V V _{CCB} =3.3~5V		0.03		pF
				V _{CCA} =1.2V V _{CCB} =5V		0.01		pF
				V _{CCA} =1.2V V _{CCB} =1.8V		0.01		pF
				V _{CCA} =1.5V V _{CCB} =1.8V		0.01		pF
				V _{CCA} =1.8V V _{CCB} =1.8V		0.01		pF
				V _{CCA} =2.5V V _{CCB} =2.5V		0.01		pF
				V _{CCA} =2.5V V _{CCB} =5V		0.01		pF
				V _{CCA} =3.3V V _{CCB} =3.3~5V		0.04		pF




■ TEST CIRCUIT AND WAVEFORMS

Load Circuit



**MAX DATA RATE, PULSE
DURATION PROPAGATION
DELAY OUTPUT RISE AND FALL
TIME MEASUREMENT**

**ENABLE/DISABLE TIME
MEASUREMENT**



Notes: 1. C_L includes probe and jig capacitance.

2. The outputs are measured one at a time, with one transition per measurement.

3. t_{PLH} and t_{PHL} are the same as t_{PD} .

4. V_{CCI} is the V_{CC} associated with the input port.

5. V_{CCO} is the V_{CC} associated with the output port.

6. All parameters and waveforms are not applicable to all devices.

■ DETAILED DESCRIPTION

Overview

The **UTXB0104** device is a 4-bit, directionless voltage-level translator specifically designed for translating logic voltage levels. The A port is able to accept I/O voltages ranging from 1.2V to 3.6V, while the B port can accept I/O voltages from 1.65V to 5.5V. The device is a buffered architecture with edge-rate accelerators (one-shots) to improve the overall data rate. This device can only translate push-pull CMOS logic outputs. If for open-drain signal translation, please refer to the **UTC UTXS010X** products.

Architecture

The **UTXB0104** architecture (see Figure 1) does not require a direction-control signal to control the direction of data flow from A to B or from B to A. In a dc state, the output drivers of the **UTXB0104** can maintain a high or low, but are designed to be weak, so that they can be overdriven by an external driver when data on the bus starts flowing the opposite direction.




Figure 1. Architecture of UTXB0104 I/O Cell

The output one-shots detect rising or falling edges on the A or B ports. During a rising edge, the one-shot turns on the PMOS transistors (T1, T3) for a short duration, which speeds up the low-to-high transition. Similarly, during a falling edge, the one-shot turns on the NMOS transistors (T2, T4) for a short duration, which speeds up the high-to-low transition. The typical output impedance during output transition is 70Ω at $V_{CCO} = 1.2V$ to 1.8V, 50Ω at $V_{CCO} = 1.8V$ to 3.3V, and 40Ω at $V_{CCO} = 3.3V$ to 5V.

Enable and Disable

The **UTXB0104** has an OE input that is used to disable the device by setting OE=LOW, which places all I/Os in the high-impedance (Hi-Z) state. The disable time (t_{dis}) indicates the delay between when OE goes low and when the outputs actually get disabled (Hi-Z). The enable time (t_{en}) indicates the amount of time the user must allow for the one-shot circuitry to become operational after OE is taken high.

■ DETAILED DESCRIPTION (Cont.)

Pull-up or Pull-down Resistors on I/O Lines

The **UTXB0104** is designed to drive capacitive loads of up to 70pF. The output drivers of the **UTXB0104** have low dc drive strength. If pullup or pulldown resistors are connected externally to the data I/Os, their values must be kept higher than 50 k Ω to ensure that they do not contend with the output drivers of the **UTXB0104**. For the same reason, the **UTXB0104** should not be used in applications such as I²C or 1-Wire where an open-drain driver is connected on the bidirectional data I/O. For these applications, use a device from the UTC UTXS01xx series of level translators.


Device Functional Modes

The **UTXB0104** device has two functional modes, enabled and disabled. To disable the device, set the OE input to low, which places all I/Os in a high impedance state. Setting the OE input to high will enable the device.

Power Supply Recommendations

During operation, ensure that $V_{CCA} \leq V_{CCB}$ at all times. During power-up sequencing, $V_{CCA} \geq V_{CCB}$ does not damage the device, so any power supply can be ramped up first. The **UTXB0104** has circuitry that disables all output ports when either V_{CC} is switched off ($V_{CCA/B} = 0V$). The output-enable (OE) input circuit is designed so that it is supplied by V_{CCA} and when the (OE) input is low, all outputs are placed in the high-impedance state. To ensure the high-impedance state of the outputs during power up or power down, the OE input pin must be tied to GND through a pull-down resistor and must not be enabled until V_{CCA} and V_{CCB} are fully ramped and stable. The minimum value of the pull-down resistor to ground is determined by the current-sourcing capability of the driver.

■ TYPICAL APPLICATION CIRCUIT



UTC assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all UTC products described or contained herein. UTC products are not designed for use in life support appliances, devices or systems where malfunction of these products can be reasonably expected to result in personal injury. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. UTC reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.